

## **Octopus Reader with Buzzer Module**



**PRODUCT** 

Product Code : PURPA0004

Dimension
Power Input : 97mm (L) x 140mm (W) x 55mm (H)

: 12V DC, 1A

Peripheral Ports : RS-232 @ 115200 bps

: • LED indicators (red and green) Feature

Built-in speaker

: Tailor casing for desktop operating environment Mounting

: No display Display

## **FUNCTION**

It is connected to a POS system with the feature of adding, deducting value and card polling.

: Transaction data containing Usage Data (UD), Audit Register (AR), and Blacklist. Storage

Communication : • All data can be transferred through serial line

Need to connect with OCL supported / compatible POS terminal

## **EXAMPLE**

: Chickeeduck Apparel • Convenience Store : 7-Eleven, Circle K • Personal Care : Mannings, Watsons

: PARKnSHOP, Wellcome, CR Vanguard Supermarket